

## Urja-Lite



**Urja-Lite** is a reverse-engineered, indigenously manufactured product from **TranzTel Technologies India**. Ergonomically designed, these intrinsically safe, light weight caplamps have been build to work reliably in hazardous workplaces like Mines, Tunnels & Forests or other challenging environments.

<u>Particulars</u>	<u>Features &amp; Parameters</u>
Model	Cordless LED caplamp, impact resistant polycarbonate body weighing 270gms.
Illumination	185Meters at 110° - 140° working angle.
Safety	IP65 / IP68. Overcharge, Overdischarge & Overcurrent protection. SOS Button.
Working Condition	-5°C - 60°C, 95% Moisture
Battery	Rechargeable Panasonic Li-on Battery of 3.6V 3300mAh 1200 charge cycles.
Discharge Time	13 hours at 6000 Lux at 1meter distance
Charging Time	8 hours at 5V DC output using our charger.
Charging Style	Magnetic Charger / Charging Racks with charge level indicator.
LED Bulb Life	50,000 Cycles

Product features / performance parameters are indicative only and subject to revision without prior notice.

